

RF Power Amplifier

Model RF5087

Solid State - High Power - Broadband - 0.01MHz – 200MHz

The RF5087 is a 250 Watt broadband amplifier that covers the 0.01 to 200 MHz frequency range. This amplifier utilizes Class AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range. An optional 'front panel controller' is available which adds many control and display facilities.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability.

Like all Laplace RF series amplifiers, the RF5087 comes with an extended multiyear warranty backed by commitment to total customer satisfaction.

Specifications @ 25°C

<u>Electrical</u>		
1	Frequency Range	0.01—200 MHz
2	Saturated Output Power	250 Watts Typical
3	Power at P1dB	175 Watts Minimum.
4	Small Signal Gain	+55 dB Minimum
5	Gain Flatness	± 2.0 dB Maximum
6	IP ₃	+60 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-15 dBc min @ 175 Watts
9	Spurious Signals	< -60 dBc typical @ 175 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	2,000 Watts Maximum
12	AC Input	100 – 240 VAC, single phase
13	RF Input	0 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	Class AB
<u>Mechanical</u>		
16	Dimensions	19" x 8.75" x 21" 5RU
17	Weight	80 Lbs.
18	RF Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	95% Non-condensing
23	Shock and Vibration	Up to 10,000' Above Sea Level



Laplace Instruments Ltd

Tudor House, Grammar School Road, North Walsham, Norfolk NR28 9JH

T: +44 (0) 16 92 40 20 70. E: tech@laplace.co.uk W: www.laplace.co.uk

FRONT PANEL CONTROLLER FEATURES

- Forward Power Monitoring (dBm or Watts)
- Reflected Power Monitoring (dBm or Watts)
- Gain Control (20 dB dynamic range of adjustment)
- Fault Status - Full Protection Of any VSWR Condition, Open or Short, into any Phase Angle
- Remote Control Access via the Ethernet, RS-232, or IEEE-488 Communications ports
- Integrated Automatic Leveling Control to allow end-user to maintain output even with variances in temperature, or input RF level
- Standby/Enable Control
- Front Panel Display for easy viewing of System Status Locally
- Keypad buttons for full local control

CIRCUIT PROTECTIONS

- Thermal Overload
- Over Current
- Over Voltage
- Open or Short VSWR Conditions (With Front Panel Controller)

CIRCUIT CONTROL (WITH FRONT PANEL CONTROLLER)

- Standby (amplifier disable)
- Gain/power setting with 20dB range
- VSWR protection Rese
- ALC On/ Off

CIRCUIT INDICATIONS (WITH FRONT PANEL CONTROLLER)

- Forward Power
- Reflected power
- VSWR Fault
- Temp Fault
- Gain Setting (VVA) percentage

RFPA SYSTEM OPTIONS

- Switched Filter Bank
- Input Power Requirements
- Ruggedized Version
- Cabinet Requirements
- Outdoor Version
- Sample Ports
- Racking Options
- Many More!



FE version shown

Ordering information:

RF5087F	RF connections on front panel
RF5087R	RF connections on rear panel
RF5087FE	RF connections on front panel with front panel control option.
RF5087RE	RF connections on rear panel with front panel control option.



Laplace Instruments Ltd

Tudor House, Grammar School Road, North Walsham, Norfolk NR28 9JH

T: +44 (0) 16 92 40 20 70. E: tech@laplace.co.uk W: www.laplace.co.uk